



# ART GLASS PENDANTS

## TUBES

### P160

Project: \_\_\_\_\_

Fixture Type: \_\_\_\_\_

Location: \_\_\_\_\_

Contact/Phone: \_\_\_\_\_

### PRODUCT DESCRIPTION

The tubular P160 inner glass shade is available in Amber Fisch, Frost, and hand-painted faux Stone and encased by a clear outer glass. 12V 50W max. JC Lamp included.

Pendant Kit includes: Quick Jack Cord Set - 78" Coaxial Cable  
 • Cordset can be shortened in the field • Glass Shade & Lamp Cover • 12V 50W JC Halogen Lamp



### ORDERING INFORMATION

Model	Mounting Adapter	Hardware Finish	Shade Finish	Example
<b>P160</b>	<b>QJ</b>	<b>STN</b>	<b>STO</b>	<b>P160QJ-STN-STO</b>
	<b>QJ</b> Pendant with Quick Jack Adapter*	<b>BRZ</b> Vintage Bronze	<b>AMF</b> Amber Fisch	
	<b>MP</b> Pendant on Single Dome MonoPoint	<b>STN</b> Satin Nickel	<b>FRT</b> Frost	
	<b>MC</b> Pendant on Single Cone MonoPoint		<b>STO</b> Stone	
	<b>MB3</b> 3X Pendants on Arched Bar			
	<b>MP3</b> 3X Pendants on Large Dome			

\*For use on Alfa Quick Jack Systems

### PRODUCT SPECIFICATIONS

#### Electrical

**Lamp:** 12V 50W max. JC Lamp included, GY6.35

**Socket:** Ceramic Bi-Pin Socket, accepts G4 and GY6.35 Lamps

#### Agency Approval

**Labels:** ETL classified to UL 1598 for use in U.S. • ETL classified to CSA C22.2 No. 250 for use in Canada.

#### Mounting Specifications

**QJ:** Supplied with Quick Jack Adapter for use on MonoTrack.


**MP:** Supplied on a Non-Quick Jack (905 type) Slim Line MonoPoint. Internal 60W Electronic Transformer. Dimmable\*.

**MC:** Supplied on a Non-Quick Jack (908 type) Cone MonoPoint. Internal 60W Magnetic Transformer. Dimmable\*.

**MB3:** 3X Pendants supplied on a Non-Quick Jack (99003 type) Triple Arched Bar MonoPoint. Internal 150W Electronic Transformer. Dimmable\*.

**MP3:** 3X Pendants supplied on a Non-Quick Jack (99014 type) Triple Large Dome MonoPoint. Internal 200W Magnetic Transformer. Dimmable\*.

### DIMENSIONS



\*Alfa recommends the use of Solid State (Electronic) Dimmers with Alfa products with Electronic Transformers. Magnetic Transformers may be dimmed with a quality Incandescent Dimmer.