


# INSTALLATION AND WIRING DIAGRAM

USA

## ORION SERIES

### ORION POWER FEED II

ART. NO. 135 911 translucent plastic



## IMPORTANT SAFETY INSTRUCTIONS



1. Read all instructions!
2. Turn off power prior to any work on the systems.
3. THIS PRODUCT MUST BE INSTALLED BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED, IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE.
4. Intergrated AC/DC converter for dimming, with AC Transformer. Max 96 Watts.
5. Suitable for outdoor use.
6. Warranty is void in case of unauthorized modifications and/ or improper use.

READ ALL OF THESE INSTALLATION INSTRUCTIONS BEFORE INSTALLING THE FIXTURE

### Contents of Delivery:

ORION POWER FEED II - qty. (1)

### Attaching Power feed to Orion Belt

1. - Align power feed cable (A) to the connection pin (B), connect both parts together. Connect the Orion Belt (C) to the other end of the connection pin.
2. - Place attached pieces into the center of the power feed cover (D) Squeeze silicon gel, which is provided, into power feed cover. Close with the other half of the power feed cover. (Note. Silicone gel required when Orion Belt is used outdoors.)
3. - Screw power feed covers together, with supplied screws (E). Wipe off excess silicon gel from the power feed cover.
4. - Place silicon gel into end cap (F) before attaching to Orion belt, wipe off excess silicon gel from end cap.

